



L118

118-512 MHz L 1/4 Wave Antenna

| Frequency Mhz | Rod Length In Inches | Frequency Mhz | Rod Length In Inches |
|------------------|-------------------------|------------------|-------------------------|
| 118 | 23-3/4" | 220 | 12-1/2" |
| 120 | 23-1/2" | 225 | 12-1/8" |
| 122 | 23" | 405 | 6-3/4" |
| 124 | 22-1/2" | 412 | 6-3/4" |
| 126 | 22" | 420 | 6-7/16" |
| 128 | 21-1/2" | 430 | 6-3/16" |
| 130 | 21-1/8" | 440 | 6" |
| 132 | 20-7/8" | 450 | 5-7/8" |
| 145 | 19-1/8" | 460 | 5-3/4" |
| 150 | 18-1/4" | 470 | 5-5/8" |
| 155 | 17-5/8" | 480 | 5-1/2" |
| 160 | 17-1/8" | 490 | 5-1/2" |
| 165 | 16-1/2" | 500 | 5-3/8" |
| 170 | 15-13/16" | 512 | 5-1/4" |
| 175 | 15-1/4" | | |

©Laird Technologies-All Rights Reserved

Tel: 847.839.6000 • Fax: 847.839.6036 • www.lairdtech.com
L:\Instruction Sheet PDF's (Shop)\ANT_IS_QW L118 0911 .pdf